

MAX® RM-8

RACK MOUNTED POWER PROTECTION AND DISTRIBUTION





TOP BENEFITS.

The RM-8 is the perfect low-cost AC power solution for many rack mount systems. Install an RM-8 in the top slot of your rack, and the eight switched AC outlets in the rear panel will power up and protect all your equipment up to a 15-amp load.

The RM-8 protects your delicate electronic equipment by combining high voltage varistor (MOV) surge and transient suppressors. The fast-acting suppression circuit quickly responds and clamps transient voltages to safe levels. An RFI/EMI interference filter works to prevent noise from fluorescent lights, certain dimmers, radio transmitters, and similar sources of "electronic pollution" from contaminating the AC line and from there, leaking into sensitive audio, video, or computer circuits. The RM-8 is NRTL/TUV listed.

RM-8 SPECIFICATIONS_

| AC Power | |
|--------------------------|--|
| Maximum Output Current:_ | 15 amps (1800 watts at 120 VAC) |
| Line Cord: | 6 ft. integrated, 14 AWG |
| Operating Voltage: | 90 to 140 VAC |
| Spike Protection Mode: | Line to neutral |
| Clamping Voltage: | 188 Vpk peak @ 3,000 Amps (133 VAC RMS) |
| Maximum Surge Current: | 4,500 amps |
| Noise filtration: Tran | sverse mode: Greater than 20dB, 1.5 to 200 MHz |

FEATURES_

■ 15 amp rating, with circuit breaker

For safety, a circuit breaker is provided on the rear panel. If the total load on the Power Conditioner (combining all outlets) exceeds the 15A (or 1800 watt limit), the circuit breaker will trip. If this happens, it may be easily reset by pushing in the button. There is no need to replace fuses.

Master switch

The RM-8 has a convenient master switch for the rear outlets which glows when the power is on.

One year limited warranty

The RM-8 is protected by a limited one year warranty covering manufacturer defects. Warranty service is provided by Furman Sound, Inc.

- Standard level of filtration
- Standard level of surge suppression
- 8 Outlets rear panel and one front panel outlet
- Sturdy one rack space design
- Rack mount ears built-in

Furman product provided for Panamax as replacement for discontinued POWERMAX® RACMAX - GRM0600-80

UPC's, QUANTITIES, WEIGHTS & MEASUREMENTS FOR ORDERING & SHIPPING _

| , . | , | | | | | | | | |
|--------------------------|--------|---------------------------|--------|-----------------|---------------|-----------------------|--------|-------------------|-----|
| MODEL RM-8 UNIT CA | | ARTON | | | MASTER CARTON | | | | |
| Dimensions | Weight | Dimensions | Weight | UPC | Qty | Dimensions | Weight | UPC | Qty |
| 1.75" H x 19" W x 7.5" D | 5 lbs | 3.5" H x 21.75" W x 9.25" | 6 Lbs | 0 50616 00804 4 | 1 | 11.5" H x 23" W x 20" | 39 Lbs | 50 050616 00804 9 | 6 |